

MPA-120



PA amplifier with 4 aux input selector and microphone with priority. Suitable for shops with background music from multiple sources and priority paging.

POWER	180 W maximum, 120 W RMS
RESPONSE	50 -16,000 Hz ± 3 dB
DISTORTION	Harmonic: < 0.5% at 1 kHz
INPUTS	4 balanced mics., XLR 2,000 Ohm 5 mV, adjustable 4 aux, 2 x RCA 10,000 Ohm 200 mV 1 amp in, RCA 10,000 Ohm 1
OUTPUTS	1 rec out, 2 x RCA 470 Ohm 200 mV 1 pre out, RCA 470 Ohm 1 V 1 mix out, XLR 47,000 Ohm 1 V
CONTROLS	Tone: bass and treble Volume: mic. 1 to 4, aux, chime and general volume
PHANTOM	48 V in mics. 1 to 4, selectable
PRIORITY	Mics. 1 to 4 through signal level, selectable Chimes on contact closure
CHIMES	2 chimes, selectable
PROTECTION	Temperature, overload, short circuit
IMPEDANCE	4 Ohm and 100, 70 and 50 V lines, euroblock
POWER SUPPLY	230 V AC, 200 W and 24 V DC, 5 A
DIMENSIONS	483 x 89 x 340 mm depth. 2 U 19" rack
WEIGHT	9.3 kg

© 2019 Copyright by FONESTAR SISTEMAS, S.A.