FONESTAR

MA-125GU



PA amplifiers with excellent performance and a variety of inputs and outputs. Suitable for shops, PA systems and distributed audio. This model has a loudspeaker zone selector incorporated with independent volume control and a USB/SD/MP3 recorder/player.

POWER	180 W maximum, 120 W RMS
RESPONSE	80-16,000 Hz ±3 dB
DISTORTION	Harmonic: < 1%
INPUTS	4 balanced mics/lines, combo (XLR and 6.3 mm jack) 600 Ohm 2 mV and 47,000 Ohm 150 mV, switchable 1 aux, 2 x RCA 47,000 Ohm 300 mV 1 amp in, RCA 10,000 Ohm 1 V 1 tel. input, screw terminals 600 Ohm 100 mV
OUTPUTS	1 line out, 2 x RCA 47,000 Ohm 1 V 1 pre out, RCA 600 Ohm 1 V 1 monitor, screw terminals 600 Ohm, 775 mV and 1 W 8 Ohm (aux input)
CONTROLS	Tone: Bass: ±10 dB Treble: ±10 dB Volume: Inputs 1-4, aux, general volume and USB/SD/MP3 player
PLAYER	USB/SD/MP3 recorder/player
PHANTOM	24 V in mics. 1 to 4, selectable
PRIORITY	Tel. input and mic.1 input level priority, selectable
ZONE SELECTOR	4 selectable loudspeaker zones with independent volume control, maximum 120 W per zone
IMPEDANCE	4 Ohm and 100, 70 and 25 V lines, screw terminals
POWER SUPPLY	230/115 V AC, 290 W and 24 V DC, 161 W
DIMENSIONS	420 x 89 x 300 mm depth. 2 U 19' rack
WEIGHT	10.2 kg
OPTIONAL	MA-2N: mounts for assembly on 19' rack

© 2020 Copyright by FONESTAR SISTEMAS, S.A.