

MA-181RU



PA amplifier with USB/SD/MP3 player and digital FM tuner. Suitable for commercial installations, PA and distributed audio.

POWER	180 W RMS
RESPONSE	Microphones: 80-18,000 Hz Aux: 50-20,000 Hz
DISTORTION	Harmonic: < 1%
S/N RATIO	Microphones: > 60 dB Aux: > 70 dB
INPUTS	2 balanced mic./line, XLR, 1 mV and 50 mV switchable 1 aux, 2 x RCA and 3.5 mm jack, 135 mV and 70 mV
OUTPUTS	1 line out, 2 x RCA, 700 mV
CONTROLS	Tone: Bass: ± 10 dB Treble: ± 10 dB Volume: inputs 1 to 2, aux/mp3, general volume and USB/SD/MP3/FM player
PLAYER	USB/SD/MP3 player and digital FM tuner with presets and auto-scan
PHANTOM	24 V in mics 1 to 2, selectable
PRIORITY	Mic. 1 and 2 through signal level
IMPEDANCE	4 Ohm and 100 and 70 V lines, screw terminals
POWER SUPPLY	230/115 V AC, 250 W
DIMENSIONS	420 x 100 x 320 mm depth. 2 U 19" rack
WEIGHT	8.3 kg
ACCESSORIES	FM antenna 2 19" rack mounts

© 2020 Copyright by FONESTAR SISTEMAS, S.A.