



## NC805D

1.2-3.6m/4-12ft tail call (connects to a QT602 call point or QT636/637 interface unit)



## Overview

An extendable coiled tail call lead for use with C-TEC's Quantec and 800 Series Call Systems.

Allows users to remotely generate Standard calls from armchairs, beds, etc.

Comprises a pear-shaped call push, coiled 1.2-3.6m trailing lead and a 6.5mm remote jack plug.

Easily connects to the 6.35mm remote socket on compatible Quantec and 800 Series call points.

Activating the pear push or removing the tail call lead from a call point's remote socket will generate a Standard call.

# Technical Specifications

---

<b>Compatibility</b>	C-TEC's Quantec and 800 Series Call Systems.
<b>Quiescent current</b>	0mA (none).
<b>Alarm current</b>	Determined by the type of control equipment and number / type of field devices connected to the system.
<b>Indicators</b>	Reassurance LED on host call point will illuminate steady when call push is activated and/or removed.
<b>Controls</b>	Red Call button (generates a Standard call on activation when connected to a compatible Quantec or 800 Series call point).
<b>Connections</b>	6.35mm (quarter inch) jack plug.
<b>Onboard Sounder</b>	No.
<b>Onboard Infrared Receiver</b>	No.
<b>Product dimensions (mm)</b>	28 W x 21 H x 74 D mm (pear push). Lead extends from 1.2-3.6m (4-12ft) long.
<b>Construction &amp; finish</b>	Plastic.
<b>IP Rating</b>	IP40.
<b>Weight</b>	124g
<b>Operating conditions/temperature</b>	-5°C to +40°C. Max. relative humidity 95% non-condensing.

---

Datasheet generated from <https://www.electrika.com> last updated Wednesday, January 16, 2019 11:45:58 AM