



QT602E

Quantec Euro call point, button reset (icon label)



Overview

A programmable addressable call point c/w iconised label and remote jack socket for use with C-TEC's Quantec Addressable Call System.

Includes a Call button, Reset button and red/green confidence light.

Can make up to 5 levels of call - Standard, Enquire, Help Required, Emergency, Presence & Attendance (dependent on configuration and ancillary devices used). Attack and Attendance calls can also be made if connected to compatible slave infrared receiver.

Remote socket allows the connection of optional tail call leads, pressure mats, etc.

Can be programmed to operate in a multitude of ways using a QT423 configurator.

Connections provided for additional slave devices such as ceiling pulls, overdoor lights, slave infrared receivers and more.

QT602EM magnetic reset version also available.

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network).
Quiescent current	Less than 3mA.
Alarm current	14mA.
Indicators	Red/green confidence LED.
Controls	Iconised Call button; Iconised Reset button. (QT602EM magnetic reset version also available).
Connections	Net +; Net -; R; G; L+; SW; IR; SLV.
Expansion connections	R; G; L+; SW; IR & SLV terminals allow the connection of optional slave overdoor lights, slave call points, slave ceiling pulls and slave infrared receivers.
Onboard 6.35mm Remote Jack Socket	Yes - for the optional connection of tail call leads/pear pushes, pressure mats and movement detectors.
Onboard Sounder	No.
Onboard Infrared Receiver	No.
Product dimensions (mm)	86 W x 86 H x 30 D mm. Can be mounted on a standard UK 25mm single gang flush or surface back box.
Construction & finish	Plastic.
IP Rating	IP20
Weight	72g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.

Datasheet generated from <https://www.electrika.com> last updated Wednesday, January 16, 2019 11:46:02 AM