

## TFA-500



100 V line transformers for amplifiers. Converts the amplifier or low impedance (4-8 Ohm) stereo power amp output into a high impedance output for loudspeakers with 100 or 70 V line transformer. It allows you to connect low impedance and 100 V line loudspeakers at the same time. Perfect for PA applications and background music where a large number of speakers need to be connected to just one amplifier.

POWER	Stereo: 500 + 500 W RMS
	Bridge mode: 1,000 W RMS
RESPONSE	20-20,000 Hz
DISTORTION	< 0.1%
PROTECTION	Temperature, over current and RF filter.
INDICATORS	Input signal.
INPUTS	2 inputs, 4-8 &#937;, screw terminals and banana sockets.
OUTPUTS	Loudspeakers: 100 and 70 V lines, screw terminals, stereo or mono bridge, selectable
DIMENSIONS	483 x 72 x 236 mm depth. Approx. 1.5 x 19' U rack.
WEIGHT	8.7 kg

© 2020 Copyright by FONESTAR SISTEMAS, S.A.