

QT608CD1S

Quantec large corridor display (965x163x68mm), needs QT615S interface



Overview

Alarge 16 character x 2 line LED display measuring965mmx 163mm making it ideal for use in long corridors, nursing stations, staff roomsandoffices.

Utilises the latest LED technology to visually informstaff of the location of incoming calls (and occupied rooms) in large, easy-to-read text.

All calls are displayed in red text exceptpresence calls which are displayed in green.

When no calls are present on the system the current time is shown in green.

Typically used in conjunction with one or more standard QT608C displays as scroll and accept buttons ARE NOT included.

Mains powered.

Connects to Quantec via a QT615 display interface unit utilising a monitored RS232 data connection.

Technical Specifications

Power requirements	Mains (PSU unit included).
Quiescent current	TBC.
Indicators	2 line x 16 character multi-LED.
Controls	None
Connections	Connects to Quantec via a QT615S display interface.
Onboard Sounder	No.
Product dimensions (mm)	965 W x 163 H x 68mm.
Construction & finish	TBC.
IP Rating	TBC.
Weight	TBC.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.

Datasheet generated from https://www.electrika.com last updated Wednesday, January 16, 2019 11:46:02 AM